

Datasheet for: ASF3000EU

Product Type: Advanced Filter Balanced Power Supply

3000VA 230v to 230v CTE with Schuko to C19 input lead, five UK sockets with Schuko adaptors & Avery Magnetics Advanced Filter System.

VA	3000
Input Voltage	230
Input Termination	16A IEC Chassis Connector
Input Current	13
amps	13
Output Voltage	230
Output Termination	Five UK 13amp 3pin sockets with Schuko adaptors.
Product Case	ASF Black Steel Powdercoated Case
Dimension	Ht:125 W:230 L:315
Weight	24kg
Primary Protection	Push to reset thermal circuit breaker SP12
Surge Protection	Relay controlled limiter in Avery filter
Product Type	Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS
Notes	Fitted with Avery Magnetics Advanced High Current Filter with inter-winding copper foil screen & 2 pole illuminated on/off switch.

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product ASF3000EU conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 24/02/2026




www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com