

## Datasheet for: ASF3000MP

### Product Type: Advanced Filter Balanced Power Supply

3000VA 230/240/250V to 230V CTE with five UK sockets & Avery Magnetics Advanced Filter System. MP model has additional input taps of 240V and 250V for use in areas with higher mains voltages.



|                    |  |
|--------------------|--|
| VA                 | 3000   |
| Input Voltage      | 230  |
| Input Termination  | 16A IEC Chassis Connector  |
| Input Current      | 13   |
| amps               | 13   |
| Output Voltage     | 230  |
| Output Termination | Five UK 13amp 3pin sockets   |
| Product Case       | ASF Black Case   |
| Dimension          | Ht:125 W:230 L:315   |
| Weight             | 24kg   |
| Primary Protection | Push to reset thermal circuit breaker SP16   |
| Surge Protection   | Electronic soft start & Avery filter   |
| Product Type       | Safety Isolating transformer Conforms to EN61558-2-6 CE & RoHS   |
| Notes              | Fitted with Avery Magnetics Advanced High Current Filter with inter-winding copper foil screen & 2 pole illuminated on/off switch. |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product ASF3000MP conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
22/12/2024


