

## Datasheet for: ASF3000MP

### Product Type: Advanced Filter Balanced Power Supply

3000VA 230/240/250V to 230V CTE with five UK sockets & Avery Magnetics Advanced Filter System. MP model has additional input taps of 240V and 250V for use in areas with higher mains voltages.



VA	3000
Input Voltage	230
Input Termination	16A IEC Chassis Connector
Input Current	13
amps	13
Output Voltage	230
Output Termination	Five UK 13amp 3pin sockets
Product Case	ASF Black Case
Dimension	Ht:125 W:230 L:315
Weight	24kg
Primary Protection	Push to reset thermal circuit breaker SP16
Surge Protection	Electronic soft start & Avery filter
Product Type	Safety Isolating transformer Conforms to EN61558-2-6 CE & RoHS
Notes	Fitted with Avery Magnetics Advanced High Current Filter with inter-winding copper foil screen & 2 pole illuminated on/off switch.

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product ASF3000MP conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
15/08/2025

