

## Datasheet for: EU-JA2000

### Product Type: Use Japanese Appliances in Europe

2000VA 230V Schuko to 100V Voltage Converter with two Japanese sockets



VA	2000
Input Voltage	230
Input Termination	3 pin Schuko plug
Input Current	8
amps	20
Output Voltage	100
Output Termination	Two 100v Japanese 3pin socket
Product Case	UKM1 Medium Grey steel case
Dimension	Ht:115 L:250 W:190 (mm)
Weight	10kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer Conforms to EN61558-2-23 CE & RoHS
Notes	2 pin Japanese plugs are compatible with the 3 pin sockets.

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product EU-JA2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
10/09/2025



www.airlinktransformers.com - VAT No. 573 1888 10  
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | sales@airlinktransformers.com