



## Datasheet for: UK-JA3000

### Product Type: Use Japanese Appliances in The UK

3000va 230v to 100v Voltage Converter with two Japanese sockets

VA	3000
Input Voltage	230
Input Termination	3 pin UK 13amp plug
Input Current	13
amps	30
Output Voltage	100
Output Notes	Max 15A load per socket
Output Termination	Two 100v Japanese 3pin socket
Product Case	UKL1 Large Grey steel case
Dimension	Ht:115 L:260 W:200 (mm)
Weight	12kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.

07/02/2023



www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5TF  
01279 431865 | sales@airlinktransformers.com