



Datasheet for: M3100

Product Type: 110v Site Transformers

10kva 3phase 400v to 6x110v tool transformer British Made

VA	10000
Input Voltage	400
Input Termination	Terminals to accept hardwired 3P + E
Output Voltage	110
Output Notes	10000va continuous rating
Output Termination	4x 16amp & 2 x 32amp Yellow sockets
Product Case	Sheet steel ventilation drip proof IP40 + IP44 Weatherproof covers over MCBs
Dimension	Depth 445mm x Width 565 x Height 605mm
Weight	80kg
Primary Protection	1 x 16A 3 pole type D MCB protecting 3phase 10kva
Secondary Protection	2 x 20 amp 2 pole type C MCB + 2 x 32 amp 2 pole t
Product Type	3Phase Safety Isolating transformer Conforms to European standard EN60898 (-25 deg C - +55 deg C)
Notes	Climate Class outdoor use

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product M3100 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
10/05/2026



www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com