

## Datasheet for: RX053

### Product Type: 110v portable Tool transformers

5kva 230v to 3x110v tool transformer

|                    |  |
|--------------------|--|
| VA                 | 5000   |
| Input Voltage      | 230  |
| Input Termination  | Mains lead   |
| Input Current      | 20   |
| Output Voltage     | 110CTE   |
| Output Notes       | 5000va Tool Rating 3000va continuous rating                    |
| Output Termination | 2x 16amp & 1 x 32amp Yellow sockets                            |
| Product Case       | 801 Tough GRP case with carrying handles IP44                  |
| Dimension          | Ht:280 W:340 D:260   |
| Weight             | 30kg   |
| Primary Protection | Push to reset circuit breaker                                  |
| Product Type       | Safety Isolating transformer Conforms to EN61558-2-6 CE & RoHS |
| Notes              | Tool transformer for intermitten use                           |



Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product RX053 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
22/12/2024



