

Datasheet for: RX053

Product Type: 110v portable Tool transformers

5kva 230v to 3x110v tool transformer

VA	5000
Input Voltage	230
Input Termination	Mains lead
Input Current	20
Output Voltage	110CTE
Output Notes	5000va Tool Rating 3000va continuous rating
Output Termination	2x 16amp & 1 x 32amp Yellow sockets
Product Case	801 Tough GRP case with carrying handles IP44
Dimension	Ht:280 W:340 D:260
Weight	30kg
Primary Protection	Push to reset circuit breaker
Product Type	Safety Isolating transformer Conforms to EN61558-2-6 CE & RoHS
Notes	Tool transformer for intermitten use



Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product RX053 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
12/05/2026





www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com