

Datasheet for: SU5000

**Product Type: 230v portable Tool** 

transformers

5000VA 110v to 230v step-up transformer with 2 x 16A Blue socket

transformer



VA 5000 Input Voltage 110

Input Termination 2 meter mains lead with 63A inline plug

Input Current 45 amps 22 Output Voltage 230

Output Notes 4000va continuous rating

Output Termination Two Blue 230v 16amp 3pin sockets

Product Case 801 Tough GRP case with carrying handle IP44

Dimension Ht:280 W:340 D:260

Weight 22kg

Primary Protection Push to reset circuit breaker SP20

Surge Protection SL35 Surge Limiter

Product Type Autowound transformer Conforms to EN61558-2-13 CE & RoHS

Notes British Built

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)







Declaration of Conformity: Airlink Transformers declare that the product SU5000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 28/11/2025

