

**Datasheet for: SU5000**

**Product Type: 230v portable Tool transformers**

5000VA 110v to 230v step-up transformer with 2 x 16A Blue socket transformer



|                    |  |
|--------------------|--|
| VA                 | 5000   |
| Input Voltage      | 110  |
| Input Termination  | 2 meter mains lead with 63A inline plug                  |
| Input Current      | 45   |
| amps               | 22   |
| Output Voltage     | 230  |
| Output Notes       | 4000va continuous rating                                 |
| Output Termination | Two Blue 230v 16amp 3pin sockets                         |
| Product Case       | 801 Tough GRP case with carrying handle IP44             |
| Dimension          | Ht:280 W:340 D:260                                       |
| Weight             | 22kg   |
| Primary Protection | Push to reset circuit breaker SP20                       |
| Surge Protection   | SL35 Surge Limiter                                       |
| Product Type       | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |
| Notes              | British Built  |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product SU5000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 21/11/2024



*R. Harris*

