# Datasheet for: EU-US2000



## Product Type: Use American Appliances in Europe

2000va 230v Schuko to 120v Voltage Convertor with two American socket

| | |
|---|---|
| VA | 2000 |
| Input Voltage | 230 |
| Input Termination | 3 pin Schuko plug |
| Input Current | 8.6 |
| amps | 16 |
| Output Voltage | 120 |
| Output Termination | Two 120v American 3pin sockets |
| Product Case | UKL1 Large Grey steel case |
| Dimension | L:280 x W:200 x H:120mm |
| Weight | 10kg |
| Primary Protection | Push to reset circuit breaker SP12 |
| Product Type | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product EU-US2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.
24/11/2026

www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com