



## Datasheet for: UK-US4000HW

### Product Type: Use American Appliances in The UK

4000va 230v to 120v Voltage Converter Hardwired



VA	4000
Input Voltage	230
Input Termination	3 Way Screw terminals
Input Current	17
amps	34
Output Voltage	120
Output Termination	3 Way Screw terminals
Product Case	P4 Industrial floor/wall mounting case IP23
Dimension	Ht:270 x W:215 x L:338 (mm)
Weight	15kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
24/06/2019



www.airlinktransformers.com - VAT No. 573 1888 10  
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5TF  
01279 431865 | sales@airlinktransformers.com