

Datasheet for: CBS2000

Product Type: Conditioning Balanced Power Supply

2000VA 230v to 230v CTE Three UK sockets



| VA | 2000 |
|--------------------|---|
| Input Voltage | 230 |
| Input Termination | IEC Mains Filter with 2mt lead & UK 13amp plug |
| Input Current | 8.6 |
| amps | 8.6 |
| Output Voltage | 230 |
| Output Termination | Three UK 13amp 3pin sockets |
| Product Case | CBS Light grey steel case |
| Dimension | Ht:115 W:220 L:280 |
| Weight | 14kg |
| Primary Protection | Push to reset circuit breaker SP8 |
| Surge Protection | SL32 Surge Limiter |
| Product Type | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |
| Notes | IEC Inlet 2-pole switch with Line filter & EMC shiels |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product CBS2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 17/09/2025

www.airlinktransformers.com - VAT No. 573 1888 10 Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478 14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS 01279 431865 | sales@airlinktransformers.com