



## Datasheet for: CBS2000AU

### Product Type: Conditioning Balanced Power Supply

2000VA 240V/250/260V to 240v CTE. Three Australian sockets.



VA	2000
Input Voltage	240
Input Termination	IEC Mains Filter with 2mt lead & Australian 16amp plug
Input Current	8.3A
amps	13
Output Voltage	240
Output Termination	Three Australian 10amp 3pin sockets
Product Case	CBS Light grey steel case
Dimension	Ht:125 W:230 L:315
Weight	16kg
Primary Protection	Push to reset circuit breaker SP12
Surge Protection	SL35 Surge Limiter
Product Type	
Standard	Safety Isolating transformer Conforms to EN61558-2
Notes	IEC Inlet with Line filter & EMC shields. 2-pole on/off switch. Additional 10/20V input taps for high voltage areas.

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product CBS2000AU conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 21/02/2026



[www.airlinktransformers.com](http://www.airlinktransformers.com) - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | [sales@airlinktransformers.com](mailto:sales@airlinktransformers.com)