

## Datasheet for: CBS3000AU

### Product Type: Conditioning Balanced Power Supply

3000VA 240v to 240v CTE. Three Australia sockets.



|                    |   |
|--------------------|---|
| VA                 | 3000  |
| Input Voltage      | 240   |
| Input Termination  | IEC Mains Filter with 2mt lead & Australian 16amp plug          |
| Input Current      | 13  |
| amps               | 13  |
| Output Voltage     | 240   |
| Output Termination | Three Australian 10amp 3pin sockets                             |
| Product Case       | CBS Light grey steel case                                       |
| Dimension          | Ht:125 W:230 L:315  |
| Weight             | 21kg  |
| Primary Protection | Push to reset circuit breaker SP12                              |
| Surge Protection   | SL35 Surge Limiter  |
| Product Type       | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |
| Notes              | IEC Inlet with Line filter & EMC shields. 2-pole on/off switch. |

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product CBS3000AU conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
11/06/2026



