

Datasheet for: CBS3000JA

Product Type: Conditioning Balanced Power Supply

3000VA 230v to 100V CTE Three Japanese Sockets



| | |
|--------------------|--|
| VA | 3000 |
| Input Voltage | 230 |
| Input Termination | IEC Mains Filter with 2mt lead & UK 13amp plug |
| Input Current | 13 |
| amps | 30 |
| Output Voltage | 100 CTE |
| Output Termination | Three Japanese 3pin sockets which also fit 2pin plugs |
| Product Case | CBS Light grey steel case |
| Dimension | Ht:125 W:230 L:315 |
| Weight | 21kg |
| Primary Protection | Push to reset circuit breaker SP16 |
| Surge Protection | MS35 Surge Limiter |
| Product Type | Safety Isolating transformer |
| Standard | Conforms to EN61558-2-6 CE & RoHS |
| Notes | IEC Inlet with line filter & EMC shield 2 pole on/off switch |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product CBS3000JA conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
07/12/2025




www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com