

Datasheet for: CBS3000JA

Product Type: Conditioning Balanced Power Supply

3000VA 230v to 100V CTE Three Japanese Sockets



VA	3000
Input Voltage	230
Input Termination	IEC Mains Filter with 2mt lead & UK 13amp plug
Input Current	13
amps	30
Output Voltage	100 CTE
Output Termination	Three Japanese 3pin sockets which also fit 2pin plugs
Product Case	CBS Light grey steel case
Dimension	Ht:125 W:230 L:315
Weight	21kg
Primary Protection	Push to reset circuit breaker SP16
Surge Protection	MS35 Surge Limiter
Product Type	Safety Isolating transformer
Standard	Conforms to EN61558-2-6 CE & RoHS
Notes	IEC Inlet with line filter & EMC shield 2 pole on/off switch

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product CBS3000JA conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
02/04/2025



