

# Datasheet for: EU-JACBS1000

## Product Type: Conditioning Balanced Power Supply

1000VA 230V to 100V CTE Two Japan 3 pin sockets with Schuko mains lead.



|                    |   |
|--------------------|---|
| VA                 | 1000  |
| Input Voltage      | 230   |
| Input Termination  | Mains lead with Schuko plug                           |
| Input Current      | 4.34  |
| amps               | 15  |
| Output Voltage     | 100   |
| Output Termination | Two Japanese 3pin sockets                             |
| Product Case       | USL2 Grey powder coated Steel case                    |
| Dimension          | Ht:120 W:190 L:260                                    |
| Weight             | 8kg   |
| Primary Protection | Push to reset circuit breaker SP8                     |
| Surge Protection   | SL32 Surge Limiter                                    |
| Product Type       | Safety Isolating transformer                          |
| Standard           | Conforms to EN61558-2-6 CE & RoHS                     |
| Notes              | IEC Inlet 2-pole switch with Line filter & EMC Shield |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product EU-JACBS1000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 22/05/2026



