

Datasheet for: WM3400

Product Type: Enclosed isolating transformers

3500VA 230v to 2x110v CTE 16amp sockets



| VA | 3500 |
|--------------------|---|
| Input Voltage | 230 |
| Input Termination | PA220 3way Screw terminals |
| Input Current | 15 |
| amps | 16 |
| Output Voltage | 110v CTE |
| Output Termination | 2 x 110v 16amp yellow sockets |
| Product Case | P4 Industrial floor/wall mounting case IP23 |
| Dimension | Ht:270 L: 338 W:215 (mm) |
| Weight | 20kg |
| Primary Protection | Push to reset circuit breaker SP10 |
| Surge Protection | SL35 30A Surge limitor |
| Product Type | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |
| Regulation | 0.03 |
| | |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product WM3400 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 07/09/2025

www.airlinktransformers.com - VAT No. 573 1888 10 Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478 14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS 01279 431865 | sales@airlinktransformers.com