

Datasheet for: SL0101

Product Type: Halogen Lighting

Transformers

100VA 230v to Single 12v

VA 100 Input Voltage 230

Input Termination Screw terminals with fuse Input Current 0.4347826086956522 amps 8.333333333333

Output Voltage 12

Output Termination 2way screw terminal
Product Case SL100 White steel case
Dimension Ht:70 L:230 W:140 (mm)

Weight 3kg Primary Protection Glass fuse

Secondary Protection SP10 Push to reset circuit breaker

Product Type Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)









Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 31/03/2025



www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com