

Datasheet for: SL0102

Product Type: Halogen Lighting Transformers

100VA 230v to 2 x 12v multi output halogen light transformer



VA	100
Input Voltage	230
Input Termination	Screw terminals with fuse
Input Current	0.4347826086956522
amps	4.17
Output Voltage	12v x 2
Output Termination	4way screw terminal
Product Case	SL100 White steel case
Dimension	Ht:70 L:230 W:140 (mm)
Weight	3kg
Primary Protection	Glass fuse
Secondary Protection	SP10 Push to reset circuit breaker
Product Type	Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.

17/05/2022

