

Datasheet for: SL0201

Product Type: Halogen Lighting Transformers



200VA 230v to Single 12v

| | |
|----------------------|---|
| VA | 200 |
| Input Voltage | 230 |
| Input Termination | Screw terminals with fuse |
| Input Current | 0.8695652173913043 |
| amps | 16.6666666666667 |
| Output Voltage | 12 |
| Output Termination | 2way screw terminal |
| Product Case | SL100 White steel case |
| Dimension | Ht:70 L:230 W:140 (mm) |
| Weight | 4kg |
| Primary Protection | Glass fuse |
| Secondary Protection | SP20 Push to reset circuit breaker |
| Product Type | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product SL0201 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
16/04/2026

