

## Datasheet for: SL0251

### Product Type: Halogen Lighting Transformers



250VA 230v to Single 12v

|                      |   |
|----------------------|---|
| VA                   | 250   |
| Input Voltage        | 230   |
| Input Termination    | Screw terminals with fuse                                       |
| Input Current        | 1.08695652173913  |
| amps                 | 20.8333333333333  |
| Output Voltage       | 12  |
| Output Termination   | 2way screw terminal   |
| Product Case         | SL100 White steel case  |
| Dimension            | Ht:70 L:230 W:140 (mm)  |
| Weight               | 4kg   |
| Primary Protection   | Glass fuse  |
| Secondary Protection | SP30 Push to reset circuit breaker                              |
| Product Type         | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product SL0251 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
23/02/2025

