



## Datasheet for: SL0301

### Product Type: Halogen Lighting Transformers

300VA 230v to Single 12v



VA	300
Input Voltage	230
Input Termination	Screw terminals with fuse
Input Current	1.3
amps	25
Output Voltage	12
Output Termination	2way screw terminal
Product Case	SL100 White steel case
Dimension	Ht:70 L:230 W:140 (mm)
Weight	4kg
Primary Protection	Glass fuse
Secondary Protection	SP30 Push to reset circuit breaker
Surge Protection	SL15 Surge Limiter
Product Type	Safety Isolating Transformer
Standard	Conforms to EN61558-2-6 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product SL0301 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 07/02/2026



[www.airlinktransformers.com](http://www.airlinktransformers.com) - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | [sales@airlinktransformers.com](mailto:sales@airlinktransformers.com)