

# Datasheet for: SL0501

## Product Type: Halogen Lighting Transformers



500VA 230v to Single 12v

|                      |   |
|----------------------|---|
| VA                   | 500   |
| Input Voltage        | 230   |
| Input Termination    | Screw terminals with fuse                                       |
| Input Current        | 2.173913043478261   |
| amps                 | 41.6666666666667  |
| Output Voltage       | 12  |
| Output Termination   | 2way ceramic screw terminal                                     |
| Product Case         | SL500 White steel case  |
| Dimension            | Ht:90 L:290 W:155 (mm)  |
| Weight               | 6kg   |
| Primary Protection   | Glass fuse  |
| Secondary Protection | SP45 Push to reset circuit breaker                              |
| Surge Protection     | SL15 Surge Limitor  |
| Product Type         | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product SL0501 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 08/07/2026



