Datasheet for: EU-JA0100



Product Type: Use Japanese Appliances in Europe

100va 230v Schuko to 100v Voltage Converter with one Japanese socket

VA	100
Input Voltage	230
Input Termination	3 pin Schuko plug
Input Current	0.4
amps	1
Output Voltage	100
Output Termination	One 100v Japanese 3pin socket
Product Case	UKS1 Small Grey steel case
Dimension	Ht:75 L:190 W:116 (mm)
Weight	2kg
Primary Protection	Self resetting thermal cutout
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product EU-JA0100 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
04/11/2026

www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com