



## Datasheet for: UK-JA3010HW

### Product Type: Use Japanese Appliances in The UK

3000va 230v to 100v Voltage Convertor Hardwired

|                    |  |
|--------------------|--|
| VA                 | 3000   |
| Input Voltage      | 230  |
| Input Termination  | Screw terminal 3way                                      |
| Input Current      | 13   |
| amps               | 30   |
| Output Voltage     | 100  |
| Output Termination | Screw terminal 3way                                      |
| Product Case       | P3 Grey steel case Wall/Floor mounting                   |
| Dimension          | Ht:244 L:270 W:170 (mm)                                  |
| Weight             | 14kg   |
| Primary Protection | Push to reset circuit breaker SP12                       |
| Product Type       | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 07/02/2023

