



Datasheet for: UK-JA4000HW

Product Type: Use Japanese Appliances in The UK

4000va 230v to 100v Voltage Convertor Hardwired



VA	4000
Input Voltage	230
Input Termination	Screw terminal 3way
Input Current	17
amps	40
Output Voltage	100
Output Termination	Screw terminal 3way
Product Case	P4 Grey steel case Wall/Floor mounting
Dimension	Ht:270 L:338 W:215 (mm)
Weight	18kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
28/02/2021



www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5TF
01279 431865 | sales@airlinktransformers.com