



## Datasheet for: BPS1000

### Product Type: Standard Balanced Power Supply

1000VA 230v to 230v CTE Two UK sockets



VA	1000
Input Voltage	230
Input Termination	IEC Socket with Supplied mains lead with 13amp plug
Input Current	4.35
amps	4.35
Output Voltage	230
Output Termination	Two UK 13amp 3pin sockets
Product Case	UKL2020 Grey powder coated Steel case
Dimension	Ht:120 W:190 L:260
Weight	10kg
Primary Protection	Push to reset circuit breaker SP10
Surge Protection	SL32 Surge Limiter
Product Type	Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product BPS1000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 14/02/2026



[www.airlinktransformers.com](http://www.airlinktransformers.com) - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | [sales@airlinktransformers.com](mailto:sales@airlinktransformers.com)