



Datasheet for: BPSJA1510

Product Type: Standard Balanced Power Supply

1500VA 230V to 100V CTE Two Japanese Nema Sockets

VA	1500
Input Voltage	230
Input Termination	IEC Socket with Supplied mains lead with 13amp plug
Input Current	6.5
amps	15
Output Voltage	100 CTE
Output Notes	To operate Japanese equipment
Output Termination	Two Japan 3pin sockets
Product Case	USL2 Grey powder coated Steel case
Dimension	Ht:120 W:190 L:260
Weight	11kg
Primary Protection	Push to reset circuit breaker SP10
Surge Protection	SL32 Surge Limiter
Product Type	Safety Isolating transformer
Standard	Conforms to EN61558-2-06 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.

29/11/2023




www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
 14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
 01279 431865 | sales@airlinktransformers.com