

Datasheet for: EU-US0100-Iso-117V

Product Type: Use American Appliances in Europe

100VA 230V to 117V Isolating Transformer with one American socket. Suitable for vintage & sensitive lower power audio equipment. Employs an inter-winding electrostatic screen to attenuate mains interference.



| | |
|--------------------|-----------------------------------|
| VA | 100 |
| Input Voltage | 230 |
| Input Termination | Schuko plug |
| Input Current | 0.43 |
| amps | 0.8 |
| Output Voltage | 117 |
| Output Termination | One US Nema 3pin socket |
| Product Case | UKS1 Small Grey steel case |
| Dimension | Ht:75 L:190 W:116 (mm) |
| Weight | 2.5kg |
| Primary Protection | Self resetting thermal fuse |
| Product Type | Isolating transformer |
| Standard | Conforms to EN61558-2-6 CE & RoHS |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product EU-US0100-Iso-117V conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
31/08/2025



www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com