

Datasheet for: EU-JA2000

Product Type: Use Japanese Appliances in Europe

2000VA 230V Schuko to 100V Voltage Converter with two Japanese sockets

VA 2000 Input Voltage 230

Input Termination 3 pin Schuko plug

Input Current 8 amps 20 Output Voltage 100

Output Termination Two 100v Japanese 3pin socket
Product Case UKM1 Medium Grey steel case
Dimension Ht:115 L:250 W:190 (mm)

Weight 10kg

Primary Protection Push to reset circuit breaker SP12

Product Type Autowound transformer Conforms to EN61558-2-23 CE & RoHS Notes 2 pin Japanese plugs are compatible with the 3 pin sockets.

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)









Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.

03/12/2025

