



Datasheet for: UK-JA0050

Product Type: Use Japanese Appliances in The UK

50va 230v to 100v Voltage Converter with one Japanese socket



VA	50
Input Voltage	230
Input Termination	3 pin UK 13amp plug
Input Current	0.2
amps	0.5
Output Voltage	100
Output Termination	One 100v Japanese 3pin socket
Product Case	White plastic case
Dimension	80x60x60 (mm)
Weight	0.7kg
Primary Protection	Self resetting thermal fuse
Product Type	Autowound transformer
Standard	Conforms to EN61558-2-13 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product UK-JA0050 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 12/02/2026



www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com