



## Datasheet for: UK-JA0250-Iso

### Product Type: Use Japanese Appliances in The UK

250VA 230V to 100V Isolating Voltage Converter with one Japanese Socket

VA	250
Input Voltage	230
Input Termination	3 pin UK 13amp plug
Input Current	1.1
amps	2.5
Output Voltage	100
Output Termination	One 100v Japanese Nema 3pin socket
Product Case	UKS1 Small Grey steel case
Dimension	Ht:75 L:190 W:116 (mm)
Weight	3kg
Primary Protection	Self resetting thermal fuse
Product Type	Isolating transformer
Standard	Conforms to EN61558-2-6 CE & RoHS

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product UK-JA0250-Iso conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
09/02/2025

