



## Datasheet for: UK-JA2000

### Product Type: Use Japanese Appliances in The UK

2000va 230v to 100v Voltage Converter with two Japanese socket

VA	2000
Input Voltage	230
Input Termination	3 pin UK 13amp plug
Input Current	8.6
amps	20
Output Voltage	100
Output Termination	Two 100v Japanese 3pin socket
Product Case	UKL1 Large Grey steel case
Dimension	Ht:115 L:250 W:190 (mm)
Weight	10kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer
Standard	Conforms to EN61558-2-13 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product UK-JA2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
31/03/2025

