



## Datasheet for: UK-JA2000

### Product Type: Use Japanese Appliances in The UK

2000va 230v to 100v Voltage Converter with two Japanese socket

|                    |                                    |
|--------------------|------------------------------------|
| VA                 | 2000                               |
| Input Voltage      | 230                                |
| Input Termination  | 3 pin UK 13amp plug                |
| Input Current      | 8.6                                |
| amps               | 20                                 |
| Output Voltage     | 100                                |
| Output Termination | Two 100v Japanese 3pin socket      |
| Product Case       | UKL1 Large Grey steel case         |
| Dimension          | Ht:115 L:250 W:190 (mm)            |
| Weight             | 10kg                               |
| Primary Protection | Push to reset circuit breaker SP12 |
| Product Type       | Autowound transformer              |
| Standard           | Conforms to EN61558-2-13 CE & RoHS |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product UK-JA2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
12/02/2026

