

Datasheet for: UK-JA2010HW

Product Type: Use Japanese Appliances in The UK

2000va 230v to 100v Voltage Converter Hardwired.

VA	2000
Input Voltage	230
Input Termination	3 Way Screw terminals
Input Current	8.6
amps	20
Output Voltage	100
Output Termination	3 Way Screw terminals
Product Case	USLHWLarge Grey steel case
Dimension	Ht:115 L:260 W:190 (mm)
Weight	8kg
Primary Protection	Push to reset circuit breaker SP10
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS



Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product UK-JA2010HW conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
16/09/2025

A handwritten signature in black ink, likely of the exporter, over a light blue grid background.

www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com