



Datasheet for: US-JA1000

Product Type: Use Japanese Appliances in America

1000VA 120V to 100V Voltage Converter with two Japanese sockets

VA	1000
Input Voltage	120
Input Termination	3 Pole US Nema Plug
Input Current	8.3
amps	10
Output Voltage	100
Output Termination	Two 100v Japanese 3pin socket
Product Case	UKM1 Medium Grey steel case
Dimension	Ht:105 L:220 W:165 (mm)
Weight	6kg
Primary Protection	Push to reset circuit breaker SP12
Product Type	Autowound transformer
Standard	Conforms to EN61558-2-13 CE & RoHS

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product CM:0500250 500va 230v to 2x50v Chassis mounted transformer conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.

29/11/2023

