

## Datasheet for: US-UK2000

### Product Type: Use UK Appliances in America

2000va 120v to 230v Voltage Converter with Two Socket



|                    |  |
|--------------------|--|
| VA                 | 2000   |
| Input Voltage      | 120  |
| Input Termination  | 3 pin American 16amp plug                                |
| Input Current      | 16   |
| amps               | 8  |
| Output Voltage     | 230  |
| Output Termination | Two UK 13amp socket 230v                                 |
| Product Case       | UKL1 Large Grey steel case                               |
| Dimension          | L:280 x W:200 x H:120mm                                  |
| Weight             | 10kg   |
| Primary Protection | Self resetting thermal cutout                            |
| Product Type       | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product US-UK2000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
14/05/2026



www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | sales@airlinktransformers.com