



## Datasheet for: US-UK3000HW

### Product Type: Use UK Appliances in America

3000VA 120V to 230V Hardwire Input Voltage Converter with Two 13A Sockets



VA	3000
Input Voltage	120
Input Termination	Hardwired (Screw terminals)
Input Current	25
amps	13
Output Voltage	230
Output Termination	Two UK 13amp socket 230v
Product Case	UKL1 Large Grey steel case
Dimension	L:280 x W:200 x H:120mm
Weight	12kg
Primary Protection	Self resetting thermal cutout
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product US-UK3000HW conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.  
18/02/2026



[www.airlinktransformers.com](http://www.airlinktransformers.com) - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | [sales@airlinktransformers.com](mailto:sales@airlinktransformers.com)