



## Datasheet for: JA-UK2500HW

### Product Type: Use UK Appliances in Japan

2500VA 100V to 230V Hardwire Input Voltage Converter with Two 13A Sockets



VA	2500
Input Voltage	100
Input Termination	Hardwired (3 x 4mm Cable)
Input Current	25
amps	11
Output Voltage	230
Output Termination	Two UK 13amp socket 230v
Product Case	UKL1 Large Grey steel case
Dimension	L:280 x W:200 x H:120mm
Weight	12kg
Primary Protection	Resettable 30A Thermal Cutout
Surge Protection	MS35 Surge Limiter
Product Type	Autowound transformer
Standard	Conforms to EN61558-2-13 CE & RoHS

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Etere Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product JA-UK2500HW conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 10/02/2026



[www.airlinktransformers.com](http://www.airlinktransformers.com) - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | [sales@airlinktransformers.com](mailto:sales@airlinktransformers.com)